# KBPC10005~KBPC1010

### SINGLE-PHASE SILICON BRIDGE RECTIFIERS

**REVERSE VOLTAGE: 50 V to 1000 V** 

**FORWARD CURRENT: 10 A** 

#### **Features**

- · Reliable low cost construction
- · Ideal for printed circuit board
- · Low forward voltage drop
- · Low reverse leakage current
- · High surge current capability

### **Mechanical Data**

· Case: KBPC

#### 1.181 (30.0) 1.102 (28.0) 673 (17.1) AC 1.181 (30.0) 1.102 (28.0) 673 (17.1) AC 1.181 (30.0) 1.102 (28.0) 673 (17.1) AC 1.181 (30.0) 1.102 (28.0) 673 (17.1) 633 (16.1)

**KBPC** 

Dimensions in inches and (millimeters)

.033 x .250

.582 (14.8)

.543 (13.8)

## **Absolute Maximum Ratings and Characteristics**

Rating at 25 °C ambient temperature unless otherwise specified. Single phase, half wave, 60 Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Symbol	KBPC	KBPC	KBPC	KBPC	KBPC	KBPC	KBPC	Units
	10005	1001	1002	1004	1006	1008	1010	
$V_{RRM}$	50	100	200	400	600	800	1000	V
$V_{RMS}$	35	70	140	280	420	560	700	V
$V_{DC}$	50	100	200	400	600	800	1000	V
I <sub>(AV)</sub>	10							Α
I <sub>FSM</sub>	200						Α	
V <sub>F</sub>	1.2						V	
I <sub>R</sub>	10 500						μΑ	
CJ	200						pF	
$R_{\theta JA}$	25						°C/W	
$R_{\theta JC}$	5						°C/W	
$T_J$ , $T_{Stg}$	- 55 to + 125							°C
	$\begin{array}{c} V_{RRM} \\ V_{RMS} \\ V_{DC} \\ I_{(AV)} \\ I_{FSM} \\ V_{F} \\ I_{R} \\ C_{J} \\ R_{\theta JA} \\ R_{\theta JC} \\ \end{array}$	Symbol         10005           V <sub>RRM</sub> 50           V <sub>RMS</sub> 35           V <sub>DC</sub> 50           I <sub>(AV)</sub> I           V <sub>F</sub> I <sub>R</sub> C <sub>J</sub> R <sub>θJA</sub> R <sub>θJC</sub> R <sub>θJC</sub>	Symbol         10005         1001           V <sub>RRM</sub> 50         100           V <sub>RMS</sub> 35         70           V <sub>DC</sub> 50         100           I <sub>(AV)</sub> I <sub>(AV)</sub> V <sub>F</sub> I <sub>R</sub> C <sub>J</sub> R <sub>θJA</sub> R <sub>θJC</sub> R <sub>θJC</sub>	Symbol         10005         1001         1002           V <sub>RRM</sub> 50         100         200           V <sub>RMS</sub> 35         70         140           V <sub>DC</sub> 50         100         200           I <sub>(AV)</sub> I <sub>FSM</sub> V <sub>F</sub> I <sub>R</sub> C <sub>J</sub> R <sub>θJA</sub> R <sub>θJC</sub>	Symbol         10005         1001         1002         1004           V <sub>RRM</sub> 50         100         200         400           V <sub>RMS</sub> 35         70         140         280           V <sub>DC</sub> 50         100         200         400           I <sub>(AV)</sub> 10         200         400           V <sub>F</sub> 1.2         10         500           C <sub>J</sub> 200         200         200           R <sub>θJA</sub> 25         5	Symbol         10005         1001         1002         1004         1006           V <sub>RRM</sub> 50         100         200         400         600           V <sub>RMS</sub> 35         70         140         280         420           V <sub>DC</sub> 50         100         200         400         600           I <sub>(AV)</sub> 10         200         400         600           V <sub>F</sub> 1.2         10         500         500           C <sub>J</sub> 200         200         200         R <sub>θJA</sub> 25           R <sub>θJC</sub> 5         5         5         5	Symbol         10005         1001         1002         1004         1006         1008           V <sub>RRM</sub> 50         100         200         400         600         800           V <sub>RMS</sub> 35         70         140         280         420         560           V <sub>DC</sub> 50         100         200         400         600         800           I <sub>(AV)</sub> 10         200         400         600         800           V <sub>F</sub> 1.2         10         500         1.2         1.2           I <sub>R</sub> 10         500         200         200         200         R <sub>θJA</sub> 25           R <sub>θJC</sub> 5         5         5         5         6         6         6         10         800	Symbol         10005         1001         1002         1004         1006         1008         1010           V <sub>RRM</sub> 50         100         200         400         600         800         1000           V <sub>RMS</sub> 35         70         140         280         420         560         700           V <sub>DC</sub> 50         100         200         400         600         800         1000           I <sub>(AV)</sub> 10         200         400         600         800         1000           V <sub>F</sub> 1.2         10         500

<sup>1)</sup> Measured at 1 MHz and applied reverse voltage of 4 VDC.





Dated : 16/07/2006 H


 $<sup>^{2)}</sup>$  Unit mounted on 8.6 X 8.6 X 0.24" thick (22 X 22 X 0.6 cm) Al, Plate.


 $<sup>^{3)}</sup>$  Unit mounted on P.C.B. at 0.375" (9.5 mm) lead length with 0.5 x 0.5" (12 x 12 mm) copper pads.

#### RATINGS AND CHARACTERISTIC CURVES









Dated: 16/07/2006 H